

## 1.1.2.7 High Power Thermal Sensors

### 1.1.2.7.3 High Power Water Cooled Thermal Sensors

#### 100W to 30kW

##### Features

- High powers
- Water cooled
- Up to 30kW
- Ø74mm aperture

30K-W-BB-74



Model	30K-W-BB-74
Use	High power up to 30kW
Measurement Type	Beam deflector + broadband absorber
Spectral Range $\mu\text{m}$	0.8 - 2
Aperture mm	Ø74mm
Power Range for Calibrated Reading	100W - 30kW
Power Noise Level	1W
Backscattered Power	~4.3% without Scatter Shield, ~1.3% with Scatter Shield <sup>(b, c)</sup>
Maximum Average Power Density $\text{kW}/\text{cm}^2$	10kW/cm <sup>2</sup> anywhere in the beam
Beam Centering Requirements	For circular beam centered within 1/4 of beam diameter. Maximum tilt angle $\pm 5$ degrees. For rectangular beam please consult Ophir representative
IMPROPERLY CENTERED BEAM CAN CAUSE DAMAGE TO SENSOR	
Response Time 0-95% typ	7s
Calibration Uncertainty $\pm\%$	1.9
Power Accuracy $\pm\%$	5 <sup>(a)</sup>
Linearity with Power $\pm\%$	2
Variation with Beam Size $\pm\%$	1 from 20 to 40 mm 1.5 from 15 to 20 mm and 40 to 45 mm
Cooling Requirements	25 liter/min at full power, proportionally less at lower power. Min flow rate 6 liter/min. Water temperature range 15-30°C. Water temperature rate of change $<1^\circ\text{C}/\text{min}$ <sup>(d)</sup>
Water Pressure Drop across Beam Absorber	Pressure drop across sensor ~0.2MPa. Pressure drop across 8 meters of 1/2" tubing with 9.5mm ID is ~0.3MPa
Water Connections	Quick connector for 1/2" OD nylon tubing <sup>(c)</sup>
Outputs	10 meter cable terminated in DB15 smart connector
Optional Accessories <sup>(c)</sup>	30K-W Scatter Shield (P/N 7Z08293) 30K-W Rubber Feet Assembly (P/N 7Z08217)
Dimensions	See drawing on next page
Weight kg	19
Compliance	CE, UKCA, China RoHS
Version	V4
Part number	<b>7Z07136</b>

Note: (a) Calibrated at 1.07 $\mu\text{m}$ . For other wavelengths in the ranges of 0.8 - 0.95 $\mu\text{m}$  & 1.1 - 2 $\mu\text{m}$  add up to  $\pm 2\%$  to the calibration error

Note: (b) When scatter shield is installed, use the 107S laser setting to compensate for the slightly higher reading. When not installed, use the 107 setting

Note: (c) For further information and options see **Accessories for High Power Sensors** on pages 113-116

Note: (d) For solutions for prolonged usage with untreated water (tap water, non DI water), please contact Ophir

\* For drawings please see page 93

30K-W-BB-74

